
MBRL20100FCT

RoHS COMPLIANT



Schottky Diodes

Features

- High frequency operation
- Low forward voltage drop
- High purity, high temperature epoxy encapsulation for enhanced mechanical strength and moisture resistance
- Guard ring for enhanced ruggedness and long term reliability
- Solder dip 275 °C max. 7 s, per JESD 22-B106

Typical Applications

Typical applications are in switching power supplies, converters, freewheeling diodes, and reverse battery protection.

Mechanical Data

- Package: ITO-220AB
- Molding compound meets UL 94 V-0 flammability rating, RoHS-compliant
- Terminals: Tin plated leads, solderable per J-STD-002 and JESD22-B102
- Polarity: As marked

■Maximum Ratings (Ta=25 °C Unless otherwise specified)

PARAMETER	SYMBOL	UNIT	MBRL20100FCT
Device marking code			MBRL20100FCT
Repetitive Peak Reverse Voltage	VRRM	V	100
Average Rectified Output Current @60Hz sine wave, R-load, Ta=25℃	IO	A	20
Surge(Non-repetitive)Forward Current @60Hz half sine-wave, 1 cycle, Ta=25°C	IFSM	А	150
Current Squared Time @1ms≤t≤8.3ms Tj=25℃	l ² t	A ² s	94
Storage Temperature	T _{stg}	°C	-55 ~ +150
Junction Temperature	Тј	°C	-55 ~ +150

■Electrical Characteristics (Ta=25°C Unless otherwise specified)

PARAMETER	SYMBOL	UNIT	TEST CONDITIONS	MBRL20100FCT
Maximum instantaneous forward voltage drop per diode	VFM	V	IFM=10.0A	0.72
Maximum DC reverse current	IRRM1	mA	VRM=VRRM T _a =25°C	0.1
at rated DC blocking voltage per diode	IRRM2		VRM=VRRM T _a =100℃	20




■Thermal Characteristics (Ta=25°C Unless otherwise specified)

PARA	METER	SYMBOL	UNIT	MBRL20100FCT
Thermal Resistance	Between junction and case	RθJ-C	°CW	4.0

■Ordering Information (Example)


PREFERED P/N	UNIT WEIGHT(g)	MINIIMUM PACKAGE(pcs)	INNER BOX QUANTITY(pcs)	OUTER CARTON QUANTITY(pcs)	DELIVERY MODE
MBRL20100FCT	Approximate 1.6	50	1000	5000	Tube

Characteristics (Typical)





Outline Dimensions



ITO-220AB				
Dim	Min	Max		
А	9.7	10.7		
В	2.15	3.25		
С	2.6	3.8		
D	14.4	15.9		
E	3.1	4.5		
F	0.4	0.8		
G	0.4	0.8		
Н	12.7	14.2		
I	1.80	2.95		
J	1.4	1.8		
К	2.1	3.56		
L	2.1	3.2		
М	3.9	5.1		

Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website http:// www.21yangjie.com , or consult your nearest Yangjie's sales office for further assistance.

3/3